

Roberts

Stream 94L

Smart Radio with Bluetooth, USB and Streaming Services
and remote control from iPhone and Android using UNDOK



Please read this guide before use

Contents

Stream 94L Smart Radio features	2	Clock and Alarms	41
Before you can use this product	3	Automatically updating the clock	41
About this instruction manual	4	Setting the clock format	41
Controls and connections	5	Manually setting the clock	42
Remote control battery replacement	7	Setting the alarm clock	43
Navigation controls	8	Snooze timer	45
Configuration	9	Disabling alarms	45
Plugging in and language selection	9	Sleep timer	46
Clock and time settings	10	Kitchen timer	46
Connecting to your computer network	11	Display and Audio	47
Manual network configuration	16	Equaliser function	47
Configuration - Using the UNDOK app	17	Brightness control	48
Network remote control options	20	Headphone socket	48
Internet Radio	21	Line out socket (3.5mm Jack)	49
Selecting a radio station by location	22	Auxiliary input socket	49
Selecting a radio station by Genre	22	Inactive Standby feature	49
Selecting a popular station	23	Information	50
Selecting a podcast	23	Factory reset	50
Presetting stations Internet radio, DAB and FM	24	Electro-magnetic compatibility advice	50
Display options - Radio / Bluetooth / USB	26	Product markings	50
Using USB memory devices	27	Software update	51
Playlists	29	Troubleshooting	53
DAB Radio	32	Cautions	55
Selecting a DAB radio station	32	Specifications	55
Finding new DAB radio stations	33	Software license information	56
Manual Tuning	33	Guarantee	57
Dynamic Range Control settings	34		
FM Radio	35		
Operating your radio in FM mode	35		
Manual tuning	35		
Stereo / Mono switching - FM	36		
Bluetooth mode	37		
Connecting Bluetooth devices	37		
Playing audio files in Bluetooth mode	38		
Connecting and reconnecting a Bluetooth device	38		
Bluetooth information	40		



Stream 94L Smart Radio features

The Roberts Stream 94L Smart Radio is a radio which provides the following features in an attractive compact unit:-

- Listen to local, regional, national and international broadcasts using FM, DAB and Internet radio
- Listen to over 1000 radio stations from around the country, and over 10,000 from around the world without using your PC.
- Listen to podcasts from a wide range of broadcasters.
- 60 radio station presets (40 Internet Radio/Podcast, 10 DAB and 10 FM).
- Playback of audio files from USB memory devices.
- MP3 format is supported.
- The Stream 94L connects to your home computer network, using WiFi connection. Dual band WiFi allows compatibility with a wide range of networks.
- WiFi Protected Setup (WPS) is supported for simpler setting up with compatible wireless routers.
- All radio station presets, network configuration details and user settings are retained in the event of a power failure.
- Your smart radio can play content from a range of streaming services.
- Supports remote control and plays music from Apple iPhone, iPad and Android devices using the UNDOK app.
- Bluetooth streaming to play your music or video soundtracks from your smartphone, tablet or similar device.
- Large clock display with time and date when in Standby.
- Two alarm timers with snooze feature to wake you to either a buzzer or a radio alarm. Adjustable sleep timer, can be set to turn the radio off after a delay of between 5 and 90 minutes.
- Menu display in a choice of languages - Danish, Dutch, English, Finnish, French, German, Italian, Norwegian, Polish, Portuguese, Spanish, Swedish, Turkish.
- Power saving Inactive Standby.
- Easy-to-read colour graphic display with an adjustable display backlight.
- Auxiliary input for playing audio from MP3 players, iPods or other audio equipment.
- Line output socket for connecting the audio signal to an external amplifier or recorder. Stereo headphone socket for private listening.
- High quality three way speaker system with bass woofer.
- Mains or battery powered using supplied mains adaptor or optional rechargeable battery pack (not included).



Before you can use this product

Before you can use your radio, you must have the following:

- A broadband Internet connection (not required for DAB, FM or Music Player functions).
- A router (or equivalent wireless access point) providing a WiFi signal, connected to your broadband Internet Service Provider. The broadband modem, router and wireless access point will often be a single combined unit supplied by your Internet Service Provider or bought from a computer store.
- A Smart phone or tablet which uses either the Android operating system (version 4.0.3 or later) or Apple iOS (version 9 or later).
- If your wireless network requires a security password to allow connection, then you either need to know the WEP, WPA or WPA2 key used for encryption so that you can get the radio to communicate with the network, or your router needs to offer WiFi Protected Setup (WPS).

The radio's WiFi system is compatible with 802.11b, g, n or a networks and can use 2.4 GHz or 5 GHz WiFi frequency bands.

When connecting using WiFi, the radio will typically work within a 10-20 metre radius from your wireless access point. The actual range achieved will depend upon the building type, other nearby wireless networks, and possible interference sources. DAB and FM radio functions can operate wherever the radio is able to receive a suitable broadcast signal.

IMPORTANT: Before you continue, make sure that your router (or access point) is powered up and working with your broadband Internet service (use your computer, smart-phone or tablet to verify this). To get this part of the system working you must refer to the instructions supplied with those items.



This instruction manual is split into sections for each of the operating modes of your Roberts Stream 94L internet radio. Each section is clearly identified by the shaded heading in the top right hand corner of each pair of pages.

Before using the Internet Radio, you will need to connect your radio to your computer network using the WiFi connection. This is covered in the section titled **Configuration**. This section also explains how to set the menu language option.

The **Internet Radio** section describes how to find radio stations to listen to. These can be radio stations that you already know and listen to conventionally, or new stations you may search for.

The section for the **USB** describes how you may play music files from USB.

The two sections for **DAB** and **FM Radio** describe how to use the radio to listen to conventional radio broadcasts.

The **Bluetooth** section describes how to use your Stream 94L to play audio files or video soundtracks directly from your smartphone, tablet or similar devices.

The section titled **Clock** and **Alarms** describes the different ways by which the clock in the radio may be set, as well as explaining the use of the alarms, snooze and sleep timer features.

The **Display** and **Audio** section shows how to adjust the display, use the equaliser and connect your radio to other audio equipment.

The **Information** section includes troubleshooting, specifications and warranty information.

Configuration

(page 9)

Internet Radio

(page 21)

USB

(page 27)

DAB & FM Radio

(page 32)

Bluetooth

(page 37)

Clock and Alarms

(page 41)

Display & Audio

(page 47)


Information

(page 50)



Controls and connections


Front view




1. Back button
2. Menu button
3. Mode button
4. Preset / Repeat / Shuffle button
5. Preset 5 / Play button
6. Preset 4 / Pause button

7. Preset 3 / Stop button
8. Preset 2 / Fast-forward button
9. Preset 1 / Rewind button
10. Info / Brightness button
11. Alarm button
12. On / Standby / Sleep button

13. Volume control
14. Remote control sensor
15. Display panel
16. Tuning / Select / Snooze control
17. Loudspeaker x 2




Rear view




- 18. Headphone socket
- 19. Line output socket
- 20. Auxiliary input socket
- 21. USB playback socket
- 22. DC input socket
- 23. Subwoofer
- 24. Telescopic aerial (antenna cable socket behind)

Remote control handset



- 1. On / Standby / Sleep button
- 2. Preset buttons 1-5 / Playback control buttons
- 3. Mode button
- 4. Info / Brightness button
- 5. Volume Down button
- 6. Volume Up button
- 7. Select / Snooze button
- 8. Tuning / Menu Up button
- 9. Menu Back button
- 10. Tuning / Menu Down button
- 11. Alarm button
- 12. Preset / Repeat / Shuffle button
- 13. Menu Forward button
- 14. Menu button



Remote control battery replacement

1. Use a tool such as a coin to remove the battery cover on the rear of your remote control. Rotate the cover approximately 45 degrees in an anti-clockwise direction to align the dot on the cover with the '⌂' marking on the remote control. Gently tap the control to release the cover.
2. Insert 1 x CR2025 size battery into the compartment with the positive side (marked +) facing towards the battery cover, as shown on the reverse side of the battery cover.
3. Close the battery cover by re-applying the cover to the control in the position marked "⌂" and then use a tool such as a coin to rotate the cover clockwise so that there is a slight click and the dot on the cover is aligned with the "⌂" marking on the remote control.
4. If the remote is not to be used for an extended period of time it is recommended that the battery is removed.

IMPORTANT: The battery should not be exposed to excessive heat such as from direct sunshine, fire or the like. After use, disposable batteries should if possible be taken to a suitable recycling centre. On no account should batteries be disposed of by incineration.

Do not leave batteries within reach of young children. They can be a choking hazard.




WARNING:

- Do not ingest the battery. Chemical Burn hazard.
- The remote control supplied with this product contains a coin/button cell battery. If the coin/button cell battery is swallowed it can cause severe internal burns in just 2 hours and can be fatal.
- Keep new and used batteries away from children.
- If the battery compartment does not close securely, stop using the product and keep it away from children.
- If you think batteries might have been swallowed or placed inside any part of the body, seek immediate medical attention.

CAUTION

Replace battery only with the same or equivalent type. Danger of explosion if the battery is incorrectly replaced.






This page describes the basic means of controlling your Stream 94L radio. Instructions for each operating mode are given in the later sections of this book.


1. Pressing the **On/Standby** button brings your radio out of Standby mode. Pressing **On/Standby** while the radio is in use will cause it to return to the Standby mode with the clock display.
2. Pressing the **Mode** button gives you access to each of the operating modes in turn. Alternatively press the **Mode** button and then turn the **Tuning/Select** control clockwise or anti-clockwise to highlight the desired menu item then press the control to select that item.
3. Pressing the **Menu** button will access the menu system.
4. Many operations require the user to make a selection from the menu. This is done using the **Tuning/Select** control. Turn the control clockwise or anti-clockwise to highlight the desired menu item then press the control to select that item.

If there are more than six items in a menu, then the display will automatically scroll up or down so that the additional items become visible. If there are many items in a menu, then the radio allows the menu to 'wrap around' in either direction. This can make it easier to reach items at the end of a long menu, such as a list of countries or Internet radio stations.
5. If an error is made when navigating the menus, it is generally possible to go back to a higher level menu by pressing the **Back** button.
6. The **Info** button allows the display of information relating to the radio station or music file being played.




Note: In this booklet, press always means **press and release**. If it is required to give a long press on a button this will be described as **apply a long press** and the button should be held down for 2 to 3 seconds until the radio has responded. Although controls on the radio are shown, all functions are also available using the remote control.



Tuning



Select/Snooze



Configuration



Plugging in and language selection

Your radio may be configured using either the display and buttons on the radio, or by using the UNDOK app.

1. Place your radio on a flat surface and plug the cable from the mains adaptor into the **DC input socket** located at the rear of your radio ensuring that the plug is pushed fully into the socket.
2. Plug the mains adaptor into a wall socket and switch on the socket.
3. **IMPORTANT:** *The mains adaptor is used as the means of connecting the radio to the mains supply. The mains socket and any multi-way mains block used for the radio must remain accessible during normal use. In order to disconnect the radio from the mains, the mains adaptor should be removed from the mains socket outlet completely.*
4. When you apply power, the display on the radio will light up and show a start up screen for a few seconds. If this is the first time that you use your radio (or after a Factory Reset) the display will show the language menu. By default your radio will display all menus and messages in English.

Note: If you wish to use UNDOK to setup your radio, please see page 17.

- 5 If you would like to setup your radio using the radio's controls instead of the UNDOK app follow the setup procedure and choose the desired language. Rotate the **Tuning** control to highlight the desired language. Press the **Tuning** control to enter the selection.
 - Your radio will then display a privacy policy. Please read the privacy policy and then press the **Tuning** control to accept the policy.
6. The radio will show a setup wizard. With 'YES' highlighted press the **Tuning** control to select 'YES' and to begin setting up your radio.
Continue on the next page.




Clock and time settings

The following instructions assume that you have just plugged in your radio and you have just specified the language option for the menus (see page 9).

1. Rotate **Tuning** to highlight the desired clock format (either 12 or 24 hour) then press the control to enter your selection.
2. Next, the way in which the radio updates its clock is set. A menu allowing you to specify the auto-update option for the clock will be shown. The 'Update from Network' option will be best for most users.
3. Rotate **Tuning** to choose an auto-update option for the clock. This can be updated from the Radio, from the Network, or not updated automatically. The default is to auto-update from the network. If you choose another option go to '[Connecting to your computer network](#)' on page 11. Otherwise you will first need to select the correct time zone and daylight savings setting, see the next steps. [If you choose 'No update' you will need to set the clock manually later. see page 42.](#) Press the control to confirm your choice.
4. Rotate **Tuning** to highlight the time zone for your current location. Press **Tuning** to enter the setting.
5. You will then need to set the Daylight Savings option according to your location (Daylight Savings is also known as Summer/Winter time or BST/ GMT adjustment).
Rotate **Tuning** to highlight 'ON' or 'OFF' as required. The asterisk shows the current setting.
In the UK, 'ON' is equivalent to British Summer Time and 'OFF' is equivalent to Greenwich Mean Time.
6. Continue setting up your radio on the next page.

Configuration



Date/Time

12/24 hour format

12

24*

Auto Update

Update from DAB

Update from FM

Update from Network *

No update

Set Timezone

UTC + 00:00: Dublin, Lond *

UTC + 00:30:

UTC + 01:00: Madrid, Am

UTC + 01:30:

UTC + 02:00: Athens, Cair

UTC + 02:30:

Daylight Savings

Daylight Savings

ON

OFF*



Connecting to your computer network

Before you can use your Stream 94L radio to listen to Internet radio, it must first be connected to your computer network.

This section of this book describes how to connect the radio to your network using the wireless (WiFi) connection.

The following instructions assume that you have just set up the clock and time options using the Setup Wizard as described on the preceding page.

These instructions also apply to the Network Wizard in the Network Settings menu (from step 2 onwards).



1. After setting the Daylight Savings options (see page 10), the display will show the 'Keep network connected?' option. You should choose 'Yes' if you wish to keep the radio connected to the network when it is in Standby mode. This will allow remote control software to switch on your radio when needed.

If you choose 'No' then your radio will shut down its WiFi connection when it is in Standby, DAB, FM, Bluetooth or Aux-in modes. This minimises power consumption but it does mean that you will need to switch the radio on manually in order to use either Streaming Services or any remote control software such as the UNDOK app.

Rotate **Tuning** to highlight the required option and then press the control to make the selection.

Your radio will then scan for available WiFi networks.

2. The radio will enter the Network Settings Wizard and will display 'Scanning...'. The radio will automatically scan both 2.4GHz and 5GHz WiFi bands. After a short while the display will show a list of the available WiFi networks. Setup using the WiFi connection, go to step 3 on the next page.




- To use a WiFi connection, you will first need to identify your network in the list of network names presented by the Network Wizard. If no networks are found then you may have to get your wireless router working (please see the instructions supplied with it) or you may be too far from the router.

When the radio finds your wireless network, it displays the Network Name (SSID) for the wireless access point on the screen. This is a name that is allocated to the access point in your router by the person who set up the network - for example: '*Jones family*' or '*Paul's network*'. Routers supplied by Internet Service Providers often have the default name of the WiFi network provided on a label or card for easy reference (e.g. BTHub - 1234, virginmedia 1234567). If the router supports WiFi Protected Setup, then '[WPS]' will be shown in front of the SSID.

It is possible, and in some locations highly likely, that your radio will find more than one wireless network, in which case you should choose which one you need to connect to.

- Rotate **Tuning** to see the SSID for each wireless network that has been found. If your network is shown proceed to step 6 on the next page. If it is *not* shown then proceed to step 5, also on the next page.

If you make a mistake at any point, use the **Back** button to go back to the previous screen.



Network Settings

Network Wizard

Scanning... /

SSID

Jones family


[WPS] Paul's network

Smith

Brown

[Rescan]

[Manual config]



Connecting to your computer network - cont.

5. If your network is not found, it may be because the router is configured not to broadcast the SSID. You should then use the **Tuning** control to highlight and select the '*Manual config*' option in order to enter the network details manually. This is described in '[Manual Network Configuration](#)', see page 16.

If your network name is being broadcast, and it was not found, then try re-scanning (press the **Back** button), and if necessary try moving your radio to a location closer to your access point / router.

6. When the SSID for the wireless network you wish to connect to is highlighted on the screen, press the **Tuning/Select** control. If WiFi Protected Setup (WPS) was indicated, you will see an additional menu at this point, otherwise proceed to step 7.

Choose one of the WPS menu options as required for your router (WPS may be via push button, or using an identification number).

'*Push Button*' - the display prompts you to press the WPS button on your router and then the **Tuning/Select** control on the radio. The two devices should then connect with the encryption key sent automatically to the radio.

'*PIN*' - the display shows an identification number which you must enter into your router using a web browser (refer to your router's user documentation). You should then press the **Tuning/Select** control on the radio. The two devices should then connect with the encryption key sent automatically to the radio.

'*Skip WPS*' - if you wish to enter the encryption key yourself (or if it was previously entered).

If you chose Push Button or PIN the screen will then show '*Connecting...*' and then '*Setup wizard completed*'. Press the **Tuning** control to exit the setup wizard and then go to paragraph 10 on the next page.

7. If your network is configured without an encryption key, the screen should say '*Connecting...*', and then '*Setup wizard completed*'. Press **Tuning** to exit the setup wizard and show the Main mode menu. If this is the case then you have successfully connected your radio to your network, so please go to paragraph 10 on the next page.

8. If the screen displays 'Key:', it is because the network is using one of the encryption systems: Wired Equivalent Privacy (WEP) or WiFi Protected Access (WPA). You will need to enter the correct WEP or WPA key into the radio to allow it to communicate with your wireless network. If you do not have the WEP or WPA key, then you should obtain it from the person who set up your network. Some wireless routers may come with an encryption key already set up by the supplier, in which case you should refer to the documentation provided with it. WPA is used here to also include WPA2.

SSID
Jones family
[WPS] Paul's network
Smith
Brown
[Rescan]
[Manual config]

SSID
Jones family
[WPS] Paul's network
Smith
Brown
[Rescan]
[Manual config]

WPS Menu
Push Button
PIN
Skip WPS

Network Settings

Please Wait

Connecting... /

Key:
0 1 2 3 4 5 6
7 8 9 . - _ @
/ a b c d e
f g h i j k l
m n o p q r s
[BkSP] [OK] [CANCEL]



WEP keys are 10 or 26 characters long (using 0 - 9, and A - F). Some wireless routers can also use pass-phrases for WEP but these are not supported by the radio. WPA keys are usually set up using a pass-phrase of between 8 and 63 characters. Your radio accepts pass-phrases for WPA keys.

- To enter the WEP or WPA key, characters are selected and entered using the **Tuning** control. As you rotate the control, the highlight scrolls through the available characters as well as the three controls on the right. The character currently highlighted will be entered when you press the **Tuning** control.

Do this as needed until the complete key has been entered. *Remember, WEP keys only use the numbers 0-9 and letters A-F. WPA keys are sensitive to upper and lower case characters. You must enter the key **exactly** or the radio will not connect to the network.*

The three controls on the right-hand side of the screen have special functions. You can quickly access these by pressing the **Info** button and then using the **Tuning** control as needed:

select '[BKSP]' to erase a character just entered (long press to clear); **Info** again to continue


select '[OK]' when the complete key has been entered

select '[CANCEL]' to cancel and re-run the Network Wizard

If a WEP or WPA key has previously been entered for the selected SSID then the display will show 'Key: [Set]'. If you have previously entered a different key, you must clear this by selecting the '[BKSP]' symbol. This will remove the '[Set]' indication.

After the final character of the WEP or WPA key has been entered, highlight the '[OK]' symbol and press the **Tuning** control. The screen will show 'Connecting...' and then 'Setup wizard completed'. Press the **Tuning** control to the exit setup wizard. The radio should now be able to connect to the network.

- Once you have connected your radio to the network (and therefore also to the Internet) it will display the Main mode menu. Press the **On/Standby** button to put the radio into Standby mode. It should then display the time as obtained from the Internet. If the time display is not correct for any reason, it can easily be adjusted later, [see page 42. 'Manually setting the clock'](#).



Connecting to your computer network - cont.

If you have followed the steps on the preceding pages successfully, your radio will have connected to your router, and then made a connection to the Internet and set its clock. You can then listen to radio stations via the internet and use the other features of your radio ([see page 21 onwards](#)).

Changing the network connection

In the sections above, you chose how your radio would be connected to your network, using a WiFi connection. From time to time, you may find that you need to connect to different computer networks. The Network Settings menu allows you to change your radio's network settings, scan for an alternative wireless network, or to manually configure the network parameters.

The steps outlined below describe how you can do this - see also the section '[Network profiles](#)' on [page 51](#). If you have no need to do this, however, [please skip to page 21](#).

Configuring the radio to use an alternative WiFi connection

1. From the Network Settings menu select '*Network wizard*'. This will present you with details of any WiFi networks that are found. Scroll down the list using the **Tuning/Select** control to the desired network name. Press the control to select this network.

The radio will then use its WiFi system to communicate with the network. Depending on the settings for the new network you may need to [enter an encryption key \(see pages 13-14\)](#). By default the radio will then acquire an IP address and other network settings from the network's router using DHCP (Dynamic Host Configuration Protocol).

Internet Radio
Last Listened >
Station List >
Recall Preset
Save Preset
Sleep
Alarms

System Settings
Equaliser >
Streaming Audio Quality
Network >
Time/Date >
Brightness >
Inactive Standby

Network Settings
Network Wizard
PBC Wlan Setup
View Settings
Manual Settings
NetRemote PIN Setup
Network Profile >

Network Settings

Network Wizard

Scanning... /



If you do not wish to use DHCP for automatic network configuration, or if your network is configured with a hidden SSID, then you will need to enter some network settings manually. The typical user will not need to use manual network configuration. The facility is provided to allow the product to be used with networks where the configuration of devices is not managed by the router, or where customised settings may be required. In such cases it is assumed that the user already has sufficient knowledge to understand the terms and settings used for this purpose. IPv4 address schemes are used.

1. From the radio's Network Settings menu, select '*Manual settings*'. You must then choose to connect using a '*Wireless*' connection. There are as many as nine settings screens, shown by the '*1 of 9*' progress marker in the top right corner of the display.

2. The subsequent menus allow configuration of the following parameters:

DHCP - On or Off

IP address - e.g. 192.168.1.25

Subnet mask - e.g. 255.255.255.0

Gateway address - e.g. 192.168.1.1

DNS address (primary and secondary addresses)

SSID - needed for WiFi connections if the SSID is not broadcast

WEP / WPA / WPA2 key and settings






When entering numbers, the SSID or the WiFi pass key, the three controls on the right-hand side of the screen have special functions. You can quickly access these by pressing the **Info** button and then use the **Tuning** control as needed:

select '[BKSP]' to erase a character just entered (long press to clear); **Info** again to continue

select '[OK]' when the complete encryption key has been entered

select '[CANCEL]' to cancel and go back to the TKIP / AES options screen

3. Upon completion of the settings the radio should connect to the network. If the connection is made successfully, the radio will return to the Network Settings menu. If the unit cannot connect, then it will display a '*Failed to connect*' message. You will then need to identify which setting may need to be changed, or whether some other network issue is responsible. Once connected, the network settings are saved. They are retained in memory while the radio is disconnected from the mains.



Configuration - Using the UNDOK app

Download the UNDOK app

Download and install the UNDOK app on to your Android or iOS device.



- iOS - Download from Apple App Store
- Android™ - Download from Google Play




- If you already have the UNDOK app installed on your device ensure that you have the latest version.
- It is possible that this app may have been changed slightly since these instructions were written.
- Please refer to the Roberts Radio website for guidance on how to use the latest version.

Note: At the time of writing Android version 4.0.3 and later or iOS version 9 or later are required to use UNDOK.



If your device uses Android, please see page 19.

The **UNDOK app** has a setup wizard to help configure suitable audio devices to connect to your home WiFi network.






1. Open the **UNDOK app**.
2. Setup a **New Audio system**.
3. The app will prompt you to use your **device's WiFi** settings to connect to your radio.
4. Select your **Stream 94L** radio. Once your device has connected to the radio, **return** to the UNDOK app.
5. Use the app to complete the setup, including giving the radio a name, how it is connected via WiFi.
6. For a WiFi connection the app will ask you to choose a WiFi network and enter the appropriate password.
7. Your radio will connect to your network.

Setup new audio system - Android device

[If your device is an iPhone or iPad \(i.e. uses iOS\) please see page 18.](#)

The **UNDOK app** has a setup wizard to help configure suitable audio devices to connect to your home WiFi network.



1. Open the **UNDOK app**.
2. Setup a **New Audio system**.
3. The app will show a list of suggested audio systems to setup.
4. Your radio will normally appear in this list as **Stream 94L**. It may appear in the list below called Other. Select the radio to be setup.
5. Use the app to complete the radio setup, including giving the radio a name.
6. Choose to connect via WiFi.
7. For a WiFi connection the app will ask you to choose a WiFi network and enter the appropriate password.
8. Your radio will connect to your network.

Note: If when setting up your radio your Android device complains that it cannot connect to the internet this is because it is temporarily connected directly to your radio. You should ignore this warning message.



Network PIN setup (PIN number)

Your radio has the option of being controlled by an application installed on an Apple iPhone, iPod touch, iPad or equivalent Android device. The PIN number facility allows you to ensure that your radio can only be controlled by your own device rather than someone else's.

The remote control application is called UNDOK, by Frontier Silicon Limited, and is available from the Apple App Store and Google Play for your device.

UNDOK will try to use the default PIN of '1234' to control your radio.

You may change the PIN if desired using the 'NetRemote PIN Setup' option in the Network settings menu. The updated PIN should then be used in the UNDOK app to allow the app to reconnect to the radio. The app will prompt you for the PIN as needed.



Control via the UNDOK app

Network Settings
Network Wizard
PBC Wlan Setup
View Settings
Manual Settings
NetRemote PIN Setup
Network Profile >

Network Settings
View Settings
Manual Settings
NetRemote PIN Setup >
Network Profile >
Clear network settings
Keep network connected

Keep network connected

Your radio has the option to shut down its WiFi connection when it is in Standby. This minimises power consumption but it does mean that you will need to switch the radio on manually in order to use either Streaming Services or any remote control software such as the UNDOK app.

If you need to be able to remotely control the radio even when it has been put into Standby, then you can choose to keep the network connected by using the 'Keep network connected' option in the network settings menu. In the Standby mode display the WiFi signal indicator is shown with or without a cross through it according to the state of the connection.

09:30
13 - 01 - 2022



09:30
13 - 01 - 2022



Internet Radio

Internet Radio - the basics

Before you can use your radio to listen to broadcasts via the Internet, it is necessary to have connected it to your computer network using the wireless (WiFi) connection. [Please see page 9 for details.](#)

There are literally many thousands of radio broadcasts available via the Internet as well as 'Podcasts'. Your radio provides several ways of searching for broadcasts in order to make finding and choosing them easier. Once you have found the radio stations that you like, you may either store them as presets within the radio. The radio allows you to store up to 40 presets.

You may search for an Internet radio station by Location. If you know the name of the station and the country from which a station is broadcast this may be the easiest method to find a station. It is also a great way to experience radio from other parts of the world.

You may also search for an Internet radio station by Genre. If you prefer a particular type of music, Blues for example, you may search for a radio station that broadcasts that type of music, and you can choose from a list of Blues radio stations regardless of location, or taking location into account.

If you know part of the name of an Internet radio station, you can enter it into the radio and it will search for stations that match that name. This can be helpful if you are unsure of the location or genre of a particular station.

The STREAM 94L radio connects to a radio station database which serves many users in many countries. This means that there is a very wide range of programme content available. You can also search for stations which have been recently added to those available (new stations) or you can search for the most popular.



Internet radio









Selecting a radio station by location

- 1. Press **On/Standby** to switch on the radio. Press **Mode** until Internet Radio is selected.
- 2. Press **Menu**.
- 3. Choose 'Station List', 'Location', and then scroll the list of continents then countries in either direction. Choose a radio category.

Note that the menu may offer one or more local selections based upon the country in which the radio is being used, according to your internet IP address ('United Kingdom' and 'BBC' stations, for example).

- 4. Highlight your chosen radio station or Podcast. Press **Tuning**.
If the radio is unable to connect to a particular radio station this may be for one of the reasons explained in ['troubleshooting' page 54](#).



Selecting a radio station by Genre

- 1. Press **Menu**. Choose 'Station List', 'UK', 'Genres', and then scroll the list of content types in either direction. Choose the desired genre.
- 2. Choose either 'All Stations' or a list of countries.
- 3. Highlight your chosen radio station. Press **Tuning**.

Searching for a radio station by name

- 1. Press **Menu**.
- 2. Choose 'Station List', then 'Search'.
- 3. To enter the search word(s) rotate **Tuning** to highlight each character for the search in turn, and press **Tuning** to enter. If you make an error rotate the control or use **Info** to access the delete character 'BKSP' on the screen and then press **Tuning**. Rotate the control or press **Info** again to go back to the character selection. After the final character of the search has been entered, use **Info** and then **Tuning** to highlight the 'OK' symbol on the screen and then press the control to finish.



Selecting a popular station

Your radio connects via the Internet to a database of radio stations. This option is provided to highlight stations which are particularly popular with listeners around the world.

1. When in Internet Radio mode press **Menu**.
2. Choose '*Station List*', '*UK*' and then '*Popular*'.
3. Highlight your chosen radio station. Press **Tuning**.

Selecting a podcast

Radio broadcasters and individuals may make programmes which are intended normally to be downloaded into a computer or copied onto a portable media player. These are commonly known as Podcasts.


1. When in Podcast mode press **Menu**. Choose '*Podcast List*'.
2. You may then search by location, genre, or using part of the name of the podcast. The searches operate in exactly the same way as when searching for a conventional radio station.
3. Stations which enable you to listen to previously broadcast programmes may allow you to fast-forward, rewind to any point within a programme and play or pause.

Note: These features are dependent on the programme or podcast and will not always be available.


Last Listened

The 'Last Listened' feature provides you with quick access to the ten most recently listened to radio stations or podcasts. As each new radio station is listened to the oldest item is deleted from the list. The Last Listened list is stored when the radio is disconnected from the mains.






1. When in Internet Radio mode, press **Menu** and then choose '*Last Listened*'.
2. The display will then show a list of the last ten Internet radio stations or podcasts. Highlight whichever you wish to listen to and then press **Tuning** to cause your radio to reconnect to that radio station or podcast.



Tuning





Select/Snooze



Your radio has 40 memory presets for Internet radio/Podcast, 10 DAB and 10 FM which can easily be set to store the details of any radio station. The first five presets may generally be accessed using the memory preset buttons 1 - 5, but these buttons are not available when listening to podcasts since they have other functions. In that case the Preset menu should be used instead (see next page). The radio station presets are retained even when the radio is switched off.



Storing a preset using the preset buttons 1-5

1. Switch on your radio and tune to the required Internet Radio, DAB or FM station.
2. To store the currently playing radio station as a preset, **apply a long press** on the required **Preset** button (1 - 5) until the display shows 'Preset stored'. The station will be stored using the chosen preset button. Repeat this procedure as needed for the remaining presets.
3. Stations that are already stored in the presets may be over-written by following the procedure described above.



Recalling a preset using preset buttons 1-5

1. Switch on your radio.
2. Select the required mode (Internet Radio, DAB, or FM) using the **Mode** button.
3. Momentarily press the required **Preset** button (1 - 5). Your radio will then connect to the station stored in the preset memory. The preset used will be shown at the bottom of the display screen.




Storing a preset using the menu

1. Switch on your radio and tune to the required Internet Radio/Podcast, DAB or FM station.
2. **Apply a long press** on the **Preset** button. The display will show a 'Save Preset' menu.
3. Use the **Tuning** control to scroll through the preset list until you reach an unused preset or a preset that you wish to change. Press and release the **Tuning** control to store the preset. '*Preset stored*' will be shown on the display. Repeat this procedure as needed for the remaining presets.
4. Stations which are already stored in the presets may be over-written by following the procedure above.



Tuning



Select/Snooze

Save Preset
 1. [Not set]
 2. BBC Radio 4
 3. Atlantic FM
 4. [Not set]
5. [Not set]
 6. BBC Radio 4




Preset Stored


Recalling a preset using the menu

1. Select the required mode (Internet Radio/Podcast, DAB or FM) using the **Mode** button.
2. Press and release the **Preset** button to display the '*Recall Preset*' menu.
3. Use the **Tuning** control to select the desired preset station. Press and release the **Tuning** control.

Your radio will then connect to the station stored in the preset memory. The preset used will be shown at the bottom of the display screen.



Tuning



Select/Snooze

Recall Preset
 1. Classic FM
 2. BBC Radio 4
 3. Atlantic FM
 4. RTL
 5. BBC Radio 2
 6. [Not set]

Internet Radio 10:30
 BBC Radio 2
 Description
 The best new music and entertainment
 5 



Your radio has a range of display options when in Internet Radio / Podcast, DAB, FM, Bluetooth and USB modes:-

1. Press the **Info** button to cycle through the various options.

Internet Radio display options

Description, genre, reliability, format, playback buffer, date.

Additional or alternative information may be displayed when listening to Podcasts.

DAB Radio display options

Station name, scrolling text, program type, multiplex name, channel & frequency, signal strength / error rate, bit rate, audio type and date.

For the signal strength/error rate a low error number indicates a better quality of DAB radio signal. The minimum signal marker 'I' which separates the left and right parts of the signal graph shows the minimum signal level required for satisfactory reception.

If a DAB broadcast provides a slideshow image, this may be viewed full screen by pressing the **Tuning** control. Press the control again to exit.

FM Radio display options

Station name, scrolling text, frequency, program type and date.





In FM mode your radio can use the Radio Data System (RDS) to display the radio station name and additional text when provided by the broadcaster and where the radio signal is sufficiently clear.

Bluetooth display options

If your connected device is able to provide information from the track being played, your radio can display the following in Bluetooth mode:- Title, album and artist details.

USB display options

Progress bar, artist, album, format and date details.



Using USB memory devices


This section describes how to use your radio to access and playback your audio files via USB memory devices. USB memory devices plug into the rectangular slot on the back of the radio.

Important: Your radio is only designed to work with USB flash memory devices. It is not intended to be connected to hard disk drives or any other type of USB device.

The Stream 94L radio has been tested with a range of USB memory devices of up to 256GB capacity. USB memory must use the FAT or FAT 32 filing system in order to operate with your radio. Your radio is unable to play from media formatted using the exFAT or NTFS formats.

It is possible to use SD, SDHC or SDXC cards for media storage and playback when held in a suitable USB adaptor. However, due to the wide variation of such adaptors, it is not possible to guarantee that all adaptor / card combinations will work in the radio.

Audio format supported is MP3.



Recommendations:

Unless you have only a few files on the USB memory device, do not place all files in the root folder.

The number of items (files / sub-folders) in any folder should be less than 2000.

Searching and playback will be more responsive if the number of files in any one folder is limited (we suggest not more than 250).

It is recommended that the USB memory is reformatted in your computer before adding your music files.

The maximum depth of folder nesting permitted is 8 folder levels (but playback is only from the currently selected level).

Shuffle and Playlist functions are limited to 500 tracks.

Cautions:

In order to minimise the risk of damage to your radio or your USB memory, please place the unit so that the memory device cannot easily be knocked while it is inserted in the socket.

Remove the USB memory before carrying the unit or if not using the USB feature for a prolonged period.

Place the unit in Standby mode before removing your USB memory device.

The USB connection is intended only for flash memory devices. The use of hard disk storage media is not supported.

Playback via USB of files stored on MP3 players is not guaranteed.



1. Carefully insert the USB memory device into the USB socket at the back of the radio. Press **On/Standby** to switch the unit on.

The radio may detect that the memory has been connected, in which case it will ask whether you wish to open the folder view of the memory contents. Press **Tuning** to select 'Yes' and skip to step 4 below.

If the USB memory was not automatically detected, proceed as follows.

2. To select USB playback mode press **Mode** as needed until the **USB** mode is selected.
3. Rotate **Tuning** until 'USB playback' is highlighted on the display and press the control. The radio will now list the content stored on the USB memory device. If there are many files or folders this may take a few seconds.
4. Rotate **Tuning** to highlight the required folder and press the control to enter the current folder. The list of tracks in the current folder will be displayed.


Alternatively, if you have nested folders (such as album folders within an artist folder) then you will simply step to the next folder level.

5. Rotate **Tuning** to select the track and press the control to begin playing from the highlighted track. All files in the current folder will then be played in turn.


Files are sorted by filename in numeric-alpha order (0 - 9 ... A - Z) before being played. Albums will play in the correct order if the filename begins with the track number (use leading zeroes if more than 9 tracks).

Controlling playback



1. Press **Pause** to pause playback of the current track.
2. If you press **Play**, playback will resume from the point where it was paused.
3. Press **Rewind** to start playback of the previous track in the list.
4. Press **Fast-forward** to start playback of the next track in the list.
5. Press and hold the **Fast-forward** or **Rewind** button to move through the current track. The longer the button is pressed, the greater the speed at which the player will move through the track. Release the button when the desired point is reached. Press **Stop** to stop playback. Press **Play** to resume playback.



Tuning



Select/Snooze








Playlists

You may wish to set up a list of music tracks or albums which can then be played as background music for a party, for example. Your radio can be configured to hold a queue of up to 500 tracks in a playlist menu. The tracks or albums for the playlist can be selected from a USB memory device. The playlist is held in the memory in your radio until the external power is removed, or until the playlist is cleared from the menu.


Adding a single track, entire album or folder to your playlist

1. When selecting (or when playing) a track using a USB memory device **apply a long press** on the **Tuning** control and the display will show 'Added to My playlist'.
2. The track will be added to the playlist for playback later.
3. When using a USB memory device highlight the chosen album, artist or folder and **apply a long press** on **Tuning**. The display will show 'Added to My playlist'.
4. Each of the tracks within the album, artist or folder selection will be added to the playlist individually. This allows any unwanted tracks to be removed from the playlist if needed (see below).



Viewing your playlist

1. Press **Mode** as needed until the **USB** mode is shown. The USB menu will then be shown on the display.
2. Choose 'My Playlist' to enter the playlist.
3. Rotate **Tuning** to scroll through the playlist.



Erasing a track from the playlist

1. Press **Menu** and then choose 'My Playlist'.
2. Rotate **Tuning** until the track you wish to erase is highlighted. **Apply a long press** on **Tuning**.
3. To delete the track rotate **Tuning** until 'YES' is highlighted, then press the control to confirm the deletion. If you do not wish to delete the track from the list rotate **Tuning** to highlight 'NO' and press the control to cancel the operation.




Clearing the playlist

1. Press **Menu**. To clear the whole playlist choose '*Clear My playlist*' and then choose 'YES'. If you do not wish to clear the playlist choose 'NO'.

Playing your playlists

1. Press **Menu**. Choose '*My playlist*'.
2. To play the playlist from a particular track, rotate **Tuning** until the desired track is highlighted then press the control to start play.
3. While playing from the playlist, you can use this function to jump to a particular track within the playlist. While playing from the playlist, you may add additional tracks or albums or remove specific tracks (please see the preceding page).




Controlling playback cont.


When playing tracks from your USB memory device you may choose to repeat the current album (or playlist), or to play the files in random order, or both options together.

Repeat tracks


1. Ensure you are in the main USB menu. Press **Menu** if needed.
2. Rotate **Tuning** until 'Repeat Play' is highlighted.
3. To activate the repeat option press **Tuning** so that 'On' appears on the display. Your selected tracks will now be played repeatedly and the **Repeat** icon will show on the display.
4. To turn off the repeat option highlight 'Repeat Play' and press **Tuning** so that 'Off' appears on the display.
5. Press **Menu** to exit.



Tuning




Select/Snooze




Play tracks in random order



1. Ensure you are in the main USB menu. Press **Menu** if needed.
2. Rotate **Tuning** until 'Shuffle play' is highlighted.
3. To activate the shuffle option press **Tuning** so that 'On' appears on the display. Your selected tracks will be played in random order and the **Shuffle** icon will show on the display.
4. To turn off the shuffle option highlight 'Shuffle play' and press **Tuning** so that 'Off' appears on the display.
5. Press **Menu** to exit.



Tuning



Select/Snooze



If both Repeat and Shuffle playback options are set to 'On' then both Repeat and Shuffle icons will be shown in the display.



1. Carefully extend the telescopic aerial. Press **On/Standby** to switch on the radio. If the radio has been used before the last used mode will be selected.
2. Press **Mode** as needed to select the DAB Radio mode.
3. If this is the first time that the DAB mode is used a scan of the Band III DAB channels will be carried out. The display will show 'Scanning'. During the scanning process, as new stations are detected the station counter will increase and the stations will be added to the list which is stored in the radio. The bar graph indicates the progress of the scan. When scanning is completed the radio will list the stations found (in numeric-alpha order 0....9....A...Z), unless it has previously tuned to a DAB station.
4. Rotate **Tuning** to scroll through the list of available DAB radio stations. Press **Tuning** to select the highlighted station. The display may show 'Connecting...' while the radio re-tunes. Use the **Volume** control to set the sound level as needed.
5. If the station list is still empty after the scan the display will show 'Service not available'. If no stations are found it may be necessary to relocate your radio to a position giving better reception.

Selecting a DAB radio station


1. When playing a DAB radio station, rotate **Tuning** to access the radio station list and to scroll through the available stations.
2. Press **Tuning**. The display may show 'Connecting...' while the radio re-tunes.

Note: A question-mark in front of the station name indicates that the station has not recently been detected by the radio.

[The use of the radio station presets is described on page 24.](#)

Secondary services

Some radio stations may have one or more additional broadcasts associated with them. If these are available, they will appear immediately after the main station as you rotate the **Tuning** control clockwise. To tune to the selected service, press **Tuning**.



Finding new DAB radio stations

Should you wish to use your radio for DAB reception in a new location, or if no stations were detected during the initial scan, you can follow this procedure to allow your radio to find out which DAB radio stations are available.

1. Press **Mode** as needed to select the DAB Radio mode.
2. Press **Menu**.
3. Choose 'Scan'.
4. Press **Tuning**. The display will show 'Scanning' and your radio will perform a scan of the Band III DAB frequencies. As new stations are found the station counter will increase and stations will be added to the list. The bar graph indicates the progress of the scan.











Manual Tuning

Manual tuning allows you to tune your radio to a particular DAB frequency in Band III. Any new stations found will be added to the station list. This function can also be used to assist the positioning of the telescopic aerial or the radio to optimise reception for a specific channel or frequency.

1. When in DAB mode, press **Menu**.
2. Choose 'Manual tune'.
3. Choose the required DAB channel. Press **Tuning**.

When the radio has tuned, the display shows the channel number and frequency, and the name of the DAB multiplex found (if any). A bar graph shows the signal strength and is useful if you need to reposition the radio or its aerial. The minimum signal marker 'I' which separates the left and right parts of the signal graph shows the minimum signal level required for satisfactory reception. Any new radio stations found on the tuned DAB multiplex will be added to the list stored in the radio.

4. Press **Menu** or **Back** to choose a different frequency.
5. Press **Menu** or **Back** a second time to access the main DAB menu.



The DRC facility can make quieter sounds easier to hear when your radio is used in a noisy environment.

1. When in DAB mode, press **Menu**.
2. Choose 'DRC' and then choose the required DRC setting (default is Off).
DRC Off - DRC is switched off, Broadcast DRC will be ignored. DRC Low - DRC level is set to 1/2 that sent by broadcaster. DRC High - DRC is set as sent by broadcaster.
3. Press **Tuning** to confirm the setting. **Note:** Not all DAB broadcasts use the DRC function. If the broadcast does not provide DRC information, then the DRC setting in the radio will have no effect.

Station order setup

Your radio has 2 station order settings from which you can choose. The station order settings are, alphanumeric and ensemble. **Note:** The default station order on your radio is alphanumeric.



1. When in DAB mode, press **Menu**.
2. Choose 'Station order' and then choose 'Alphanumeric' (list alphabetically), 'Ensemble' (organised by DAB multiplex).

Prune stations

If you move to a different part of the country, some of the stations which were listed may no longer be available. Also, from time to time, some DAB services may stop broadcasting, or may change location or frequency. Stations which cannot be found, or which have not been received for a very long time are shown in the station list with a question mark. The Prune stations function will delete the marked DAB stations from your station list.

1. When in DAB mode, press **Menu**.
2. Choose 'Prune' and then choose 'YES' to cause the invalid station names to be removed from the station list. If you do not wish to prune stations choose 'NO'.


Note: If you have moved your radio to a different part of the country you should also carry out a search for new stations ([please see the section 'Finding new stations' on page 33](#)).



FM Radio

Operating your radio in FM mode

1. Carefully extend the telescopic aerial and press **On/Standby** to switch on the radio.
2. Press **Mode** as needed to select the FM Radio mode.
3. Rotate **Tuning** in a clockwise direction. The displayed frequency will increase. Press **Tuning** to carry out an auto-tune. Your radio will scan up the FM band from the currently displayed frequency and will stop scanning when it finds a station of sufficient strength.
4. The display will show the frequency of the signal which has been found. If RDS information is available, after a few seconds the display will show the radio station name.
If you only hear hiss or interference, simply press **Tuning** to scan further. Your radio may have found a spurious interference signal.
5. To find more FM stations press **Tuning** to repeat the scan operation. To scan down in frequency, rotate **Tuning** in an anti-clockwise direction first and then press the control. Your radio will scan down the FM band from the currently displayed frequency and will stop scanning when it finds a signal of sufficient strength.
6. When the end of the waveband is reached your radio will recommence tuning from the opposite end of the waveband.
7. Use the **Volume** control to adjust the sound level as needed.



Manual tuning

1. Rotate **Tuning** to tune to a station. The frequency will change in steps of 50kHz.
2. Adjust the volume.



Scan sensitivity setting - FM

Your radio will normally scan for FM broadcasts which are strong enough to give good reception. However, you may wish the Auto-scan function to also be able to find weaker signals, possibly from more distant radio transmitters. Your radio includes a local / distant option for the Auto-scan function.

1. When in FM mode, press **Menu**.
2. Choose 'Scan Setting'.
3. To set your radio so that only the stations with the strongest signals are found during scanning choose 'YES'. (Normally this will restrict scanning to local transmissions).
4. Alternatively, to set your radio so that all available stations are found during scanning (local and distant transmissions) choose 'NO'.


Note: The initial setting (out of the box, or after a System Reset) causes the radio to ignore weaker (or more distant) signals.

Stereo / Mono switching - FM

Your radio will play stereo FM broadcasts in stereo provided that the received signal is of adequate strength. However, as a stereo signal becomes weaker the audio signal will become poorer.

It may be preferable to force the radio to play the station in mono in order to reduce the level of background hiss.

1. Ensure your radio is in FM mode and tune to the required FM station.
2. To change the audio setting, press **Menu**.
3. Choose 'Audio Setting'. The current audio setting is indicated with an asterisk. To switch to mono in order to reduce the hiss from a weak FM signal choose 'YES' or choose 'NO' to return to the normal automatic 'stereo or mono' setting.




Bluetooth mode

The Bluetooth mode on your radio allows you to play audio, play sound from video files and stream music from Bluetooth capable devices such as your mobile phone, computer, tablet etc. through your radio's loudspeakers.


- When a Bluetooth enabled device such as your Stream 94L Radio is in a 'discoverable' state other Bluetooth devices can detect, pair with or connect to it.
- 'Bluetooth pairing' occurs when two Bluetooth enabled devices agree to establish a connection and communicate with each other.

Connecting Bluetooth devices

1. Ensure that the Bluetooth capability on your phone, tablet or PC is enabled. You may need to refer to the user documentation for your device, since the method will vary with each device.
2. Ensure your radio is switched on.
3. Press the **Mode** button on your radio until the Bluetooth mode is selected. Your radio will show that it is 'discoverable' and the **Bluetooth indicator** will flash on the display. If the indicator is not flashing, then the radio is already connected to another device. To cause the radio to become 'discoverable', press **Menu** and then choose 'Disconnect'. Press **Tuning**. Your Stream 94L will become discoverable by other devices.
4. Using the Bluetooth settings of your phone, tablet or PC direct it to search for 'discoverable' devices. After a few seconds, you should see a device named '*Stream 94L*'. Just occasionally it may take longer for the radio to be found by your device.
5. Select '*Stream 94L*' to cause your phone, tablet or PC to pair with your radio and to establish a connection.
6. Once the connection is established the Bluetooth indicator will remain steady. You can now begin playing music from your smart-phone, tablet, etc.




Some Bluetooth devices may require a 'Passkey' (an authentication key) in order to establish a link between devices. A passkey is similar to a password, although you only need to use the passkey once to establish a link. If your device asks for a passkey to be able to pair with your radio then enter a code of 0000 (four zeroes).



When you have successfully connected your radio with your chosen Bluetooth device you can start to play your music using the controls on the device.

1. Once playing has started adjust the volume to the required setting using the **Volume** control on your radio or the connected Bluetooth device. The volume setting on your device and the radio are linked so you can use the control that is the most convenient.
2. The audio player in your phone, tablet or PC may be able to respond to the **Play**, **Pause**, **Next** track, **Previous** track buttons on the radio.

Note: Not all player applications or devices may respond to all of these buttons.



Connecting and reconnecting a Bluetooth device

You can only have one Bluetooth device connected to the radio at any one time although it may be paired with several devices. Once you have a Bluetooth enabled device connected to your radio it cannot be interrupted by another Bluetooth device unless you choose to break the connection.


1. To connect to a different device, press **Menu** and then choose '**Disconnect**'. Press **Tuning**. The **Bluetooth indicator** flashes.
2. Your Stream 94L radio will become '**discoverable**' by other devices.
3. You can now pair the radio with a new device using its Bluetooth settings the radio will be listed as '**Stream 94L**'. When the new Bluetooth connection has been established the **Bluetooth indicator** will remain steady. You may then play music from the new device through the radio.
4. If you no longer want your Bluetooth device to be paired with your radio you will need to delete the '**Stream 94L**' pairing on the device. Please refer to the device's Bluetooth documentation.




Disconnecting a Bluetooth device

You may disconnect your Bluetooth device using the Bluetooth menu.


1. To disconnect your Bluetooth device, press **Menu**, then choose '*Disconnect*' and then choose 'YES'. Your radio will become 'discoverable' by other devices.



Tuning




Select/Snooze



Clear Bluetooth Pairing



You may clear a Bluetooth pairing using the Bluetooth menu.

1. To clear a Bluetooth pairing, press **Menu**, then choose '*Clear Pairing*' and then choose 'YES'. Your radio will become 'discoverable' by other devices.



View Bluetooth connection details

1. To view the details of the currently connected Bluetooth device, press **Menu**, then choose '*View Details*' and then choose the desired option.



Bluetooth connectivity performance may vary depending on the connected Bluetooth devices. Please refer to the Bluetooth capabilities of your device before connecting to your radio. All features may not be supported on some paired Bluetooth devices.

A Bluetooth connection can provide a link for audio up to a distance of approximately ten metres. When pairing two Bluetooth enabled devices, for convenience, we recommend they should be no more than 2 to 3 metres apart. The presence of other functioning Bluetooth devices during connection may lead to operational difficulties.

Bluetooth is a short-range radio communication system and generally Bluetooth devices can communicate with each other clearly within a regular sized room or office. The reliability of a Bluetooth connection between different rooms will greatly depend upon the construction of the building.

Bluetooth communication range may be substantially reduced if the signal passes through a solid object. Human bodies, brick and concrete walls, heavy furniture or bookcases will all reduce the operational range of your Bluetooth devices to a greater or lesser extent. Glass, dry-wall or wood paneled walls and office partitions may have a less severe but noticeable effect. Metal pipes, foil-lined plasterboard, metal window frames and domestic wiring can also have an effect. You should position your Bluetooth devices closer to each other if you observe communication difficulties.

WiFi networks and cordless phones generally use similar radio frequencies to Bluetooth and may interfere with one another. If any interference is noticed, then try relocating the radio or one of the other devices.

The Bluetooth capabilities of your radio enable it to receive audio from many Bluetooth capable devices including mobile phones, personal computers and tablets. Only one Bluetooth device can be connected to your radio at a time. It supports the following Bluetooth profiles and functionality.

- Your radio supports A2DP (Advanced Audio Distribution Profile) which is a stereo audio connection that streams stereo music from PCs, mobile phones etc. SBC audio codec is supported.
- Your radio supports AVRCP (Audio Video Remote Control Profile) which allows your radio to control music playback from the connected device.

Note: Some mobile phones may temporarily disconnect from your radio when you make or receive calls. Some devices may temporarily mute their Bluetooth audio streaming when they receive text messages, emails or for other reasons unrelated to audio streaming. Such behaviour is a function of the connected device and does not indicate a fault with your radio.

Note: If the unit is in the Bluetooth mode and it is not connected to a Bluetooth device for more than 15 minutes it will automatically switch to the standby mode. The LCD will revert to the standby mode clock display. To use the radio again, simply press the On/Standby button to switch it on.



Clock and Alarms

Automatically updating the clock

Your radio will normally update the clock automatically when connected to the internet.

Alternatively you may specify that the time is not automatically updated. In this case the clock must always be set manually after a power interruption.


1. With your radio switched on, press **Menu**.
2. Choose '*System Settings*', '*Time/Date*', '*Auto Update*' and then choose an update option from '*Update from Radio*', '*Update from Network*' or '*No update*' as required.

Setting the clock format


The clock display used in Standby mode and on the playing mode screens can be set to 12 or 24 hour format. The selected format is then also used when setting the alarms.

1. With your radio switched on, press **Menu**.
2. Choose '*System Settings*', '*Time/Date*', '*Set Format*' and then select either 12 or 24 hour. The current clock display format is marked with an asterisk.






If the 12 hour clock format is chosen, the radio will then use the 12 hour clock for the setting of alarms, and will display a 12 hour clock with an AM or PM indicator when in standby mode.



Tuning



Select/Snooze



Manually setting the clock

After a connection to the Internet has been established, your radio will normally set its clock automatically to the local time zone that was specified during setup (see page 10). Should you need to set the time manually, change the time zone, or manually switch from winter to summer time (from GMT to BST in the UK, also commonly known outside the UK as daylight savings time), then please follow this procedure.


1. With your radio switched on, press **Menu**.
2. Choose 'System Settings'.
3. To change the current time or date setting choose 'Time/Date', 'Set Time/Date', and then set the correct day, month, year, hour and minute digits.
To change the time zone setting go to step 5.
To change from winter to summer time go to step 6.
4. The display will then return to the previous menu.
5. Select 'Set timezone' and choose the time zone which is applicable to your location.
6. Select 'Daylight savings'. The asterisk shows the current setting.
In the UK, ON is equivalent to British Summer Time, OFF is equivalent to Greenwich Mean Time.
7. Choose 'ON' or 'OFF' as required. Press **Menu** to exit.

Clock style

Your radio's standby display can be set to the analogue or digital clock style.

1. With your radio switched on, press **Menu**.
2. Choose 'System Settings', 'Time/Date' and then 'Clock style'.
3. To select the digital clock style choose 'Digital' or to select the analogue clock style choose 'Analogue'. The current style will become visible when the radio is put into standby.

Clock and Alarms



Setting the alarm clock

Your radio has two separate alarms which can be set to wake you to either the radio or a buzzer alarm. In the event of a power interruption your radio has built in memory that will retain your alarm settings. Ensure that the time is set correctly before setting the alarms.

Alarms may be set while the radio is in standby mode or switched on.

1. To change the states of the alarms while the radio is in *Standby* press the **Alarm** button. The display will cycle through No Alarm, Alarm 1 enabled, Alarm 2 enabled or Alarms 1 and 2 enabled.
2. To change the alarm settings *while the radio is in Standby*, **apply a long press** on the **Alarm** button. This will cause the Alarms menu to be displayed. Then skip to step 5 below.
3. To change the alarm settings *while the radio is switched on*, either press and release the **Alarm** button and then skip to step 5 below, or alternatively press **Menu**. Choose 'Alarms'.
4. The current alarm settings will be displayed. If no change is required, press the **Menu** or **Back** buttons to exit.
5. Choose alarm (1 or 2).
6. Choose 'Time' and then choose the alarm hour and then the alarm minute.
If the radio has been set to use a 12 hour clock format, there will also be an option here for setting AM or PM for the alarm time.
7. The display will then return to the alarm setting menu.
8. Choose 'Enable'. The display will show the Frequency options for the alarm. The alarm frequency options are as follows:




'Off' - the alarm will be disabled

'Daily' - the alarm will sound everyday

'Once' - the alarm will sound once

'Weekends' - the alarm will sound only at weekends

'Weekdays' - the alarm will sound on weekdays only



Internet Radio
Last Listened >
Station List >
Recall Preset
Save Preset
Sleep
Alarms

Alarms
Alarm 1: Off [00:00]
Alarm 2: Off [00:00]
Kitchen Timer

Alarm 1
Enable: Off
Time: 00:00
Mode: Buzzer
Volume: 20
Save

Alarm 1 time
07 : 00

Alarm 1
Enable: Off
Time: 07:30
Mode: Buzzer
Volume: 20
Save

Alarm 1 frequency
Off
Daily
Once
Weekends
Weekdays




9. Choose the alarm frequency option. Choosing Off will disable the alarm.
If you choose to set the alarm to Once you will also need to set the date.
10. The alarm can be set to buzzer, Internet radio, DAB radio or FM radio. For whichever radio mode is selected, the radio alarm may be set to any of the stations which have been stored as presets or to the station most recently listened to.
Choose the '*Mode*' option for the alarm either '*Buzzer*' or the required radio mode.
11. If setting the alarm to a radio option, choose the '*Preset*' option.
Choose from either the radio station '*Last listened*' to, or from the presets. Scroll to the chosen option and press the control to confirm the selection.
Note: The alarm may only use a preset which has already been stored.
12. Choose the '*Volume*' option. The radio uses the saved volume setting for each alarm when it sounds. Use the **Tuning** control to set the required volume setting.
13. In order to store the alarm settings select the '*Save*' option. Press **Tuning**. Your radio will show '*Alarm saved*' and will then go back to the list of alarms with the new alarm setting shown in the display.

If you decide not to save the settings, press **Back**. The display will show '*Save changes*' with a 'YES' or 'NO' option. Choose 'NO'. '*Alarm not saved*' will show on the display.

Active alarms are shown using small alarm indicators on the playing displays and on the clock display when in Standby. **Note:** If you make a mistake, use the **Back** button to go back to the previous screen.

When the alarm sounds

The buzzer or radio alarm will sound at the selected times for up to 60 minutes unless cancelled. The volume used for the alarm will be as specified during the alarm setting procedure. If the radio cannot connect to the specified DAB radio station, the buzzer alarm will be used instead.



Alarm 1 date/time

17 - 01 - 2022
13 : 53

Alarm 1 mode

Buzzer
Internet Radio
DAB
FM

Alarm 1 preset

Last Listened
1. BBC Radio 2
2. Rock Antenne
3. Absolute Radio
4. [Not set]
5. [Not set]

Alarm 1

Enable: Once
Time: 07:30
Mode: Buzzer
Volume: 20
Save




Alarm
Saved



When the alarm sounds cont.



1. During an alarm, the alarm icon will flash on the display. The radio will automatically revert to standby mode after 60 minutes.
2. To cancel an alarm, press **On/Standby** to return to Standby mode.



Note: If the radio is switched on because of an alarm you can control basic functions such as volume and selecting presets. You cannot perform operations which involve the **Tuning/Select** control since this also acts as the Snooze button (see below).



Snooze timer

1. The buzzer or radio alarm can be silenced for 5 minutes by pressing the **Tuning/Select/Snooze** control. Should you wish for a longer snooze duration this can be extended. Rotating the control while the radio is snoozed will set the available snooze time to 5, 10, 15 or 30 minutes.
2. While the snooze timer is active the remaining snooze time is shown next to the flashing alarm icon on the clock display.
3. In order to cancel the Snooze timer while the alarm is suspended, press **On/Standby**. The display will briefly show an 'Alarm Off' message.



Disabling alarms

1. To disable an alarm while the radio is in standby mode press and release the **Alarm** button to cycle through the alarm on-off options ([see page 43, step 1](#)).
2. To disable an alarm while the radio is playing enter the Alarms menu ([see page 43, steps 3 and 4](#)) and select alarm (1 or 2).
3. Choose 'Enable' and choose the 'Off' option.
4. Choose the 'Save' option and press **Tuning** to save the new setting.
The chosen alarm will now be disabled.





Alarm 1
Enable: Off
Time: 07:30
Mode: Buzzer
Volume: 20
Save




Sleep timer

Your radio can be set to turn off after a preset time has elapsed. The sleep timer can be set while the radio is in Standby or whilst in use. The sleep timer setting can be adjusted between 15 and 90 minutes.

1. **Apply a long press** on the **On/Standby** button to access the sleep timer. Select the required sleep time. The sleep timer can be set to between 15 and 90 minutes, or to Off. Press **Tuning** to confirm.
2. If the radio was in standby the radio will then be switched on for the chosen duration. If the radio was already playing then it will continue playing and the sleep timer will be set to the chosen duration. An active sleep timer is shown using a small timer indicator at the bottom of the playing displays. This indicator also shows the sleep time remaining before the radio switches itself into Standby mode.
3. To set the sleep time using the menu, press **Menu** and then choose 'Sleep' and then the required sleep time. Press **Tuning** to confirm the setting.
4. To cancel the sleep time before the preset time has elapsed and to turn off the radio, press **On/Standby** to turn the unit off manually. To cancel the sleep timer and leave the radio playing, go back into the sleep timer settings (steps 1 above) and select the Off option.



Tuning



Select/Snooze

Clock and Alarms

Set Sleep Time



15 minutes




Kitchen timer

The Kitchen Timer allows you to set the radio to alert you after a pre-determined interval (up to 5 hours in 1 minute increments). The kitchen timer can be set while the radio is in Standby or whilst in use.

1. To change the kitchen timer settings while the radio is in standby, **apply a long press** on the **Alarm** button. If the radio is in use, press the **Alarm** button. This will cause the Alarms menu to be displayed. Then skip to step 3 below.
2. To access the kitchen timer using the menu, press **Menu**. Choose 'Alarms'.
3. Choose 'Kitchen Timer' and then the required kitchen timer setting. The kitchen timer can be set to between 1 and 300 minutes, or to Off.
4. An active kitchen timer is shown on the display. The indicator also shows the time remaining. When the selected time has elapsed, the buzzer will sound.
5. To cancel the buzzer when it sounds press **On/Standby** or choose Off in the timer settings.



Tuning



Select/Snooze



Display and Audio


Equaliser function

The sound on your radio can be adjusted to suit your personal taste for the material that you are listening to. The Stream 94L has a range of equaliser modes. Alternatively you may set the treble and bass levels to your own preferences which can be accessed from the *My EQ* menu item.


1. With your radio switched on, press **Menu**.
2. Choose 'System Settings', 'Equaliser' and then cycle through and highlight the various mode. Press **Tuning** to confirm your selection.

'Normal', 'Flat', 'Jazz', 'Rock', 'Movie', 'Classic', 'Pop', 'News', 'My EQ'






The currently selected mode is marked with an asterisk.



Tuning



Select/Snooze




Setting up your My EQ profile

If you find the preset equaliser functions not to your liking, you may set up a custom treble and bass setting as follows:

1. Follow steps above in order to enter the Equaliser menu.
2. Choose 'My EQ profile setup' then 'Bass or Treble'.
3. Choose the desired level (between -14 and +14). The sound will change as you turn the tuning control. Press the control when you are happy with the bass or treble setting.
4. Press **Back** and the display will prompt you to save the changes. If you wish to save the changes choose 'YES'. If you do not wish to save the changes choose 'NO'. Press **Tuning**.
5. To use the 'My EQ' profile choose 'My EQ'.

To quickly cancel the effect of the 'My EQ' profile choose 'Normal'.

The treble and bass settings will be remembered for the next time that you wish to use the 'My EQ' setting.



Brightness control

The brightness of the display can be adjusted for when the radio is in standby and for when it is in use. If you use the unit in the bedroom, you may prefer a lower standby brightness level than the standard setting. There are 4 Standby brightness levels and 3 levels for when the radio is in use. To change the current brightness setting please follow these steps.

1. **Apply a long press** on the **Info** button to access the display brightness setting.
2. Choose either the High, Medium or Low brightness level. Press the **Tuning** control to set the level. If the radio is playing, then the chosen brightness will be applied immediately. If the radio is in standby, then the chosen brightness will be applied after a 10 second delay.
3. To set the display brightness using the menu press **Menu**.
4. Choose 'System Settings' and then 'Brightness'.
5. To adjust the display brightness when the radio is switched on select 'Normal'. To adjust the display brightness when the radio is in standby select 'Standby'. Press **Tuning**. The current setting will be marked with an asterisk.
6. Choose either the High, Medium or Low brightness level. Press the control to set the level. Press the **Menu** button to exit.

When the radio is in Standby mode, pressing a button or turning a rotary control will cause the radio to switch to the high brightness level for a few seconds. This is so that even if the standby brightness level is set low, it is still possible to see the time when needed.



Headphone socket

A 3.5mm **Headphone Socket** located on the rear of your radio is provided for use with headphones. Inserting a plug automatically mutes the internal loudspeaker. Please be aware that the sensitivity of headphones can vary widely. We therefore recommend setting volume to a low level before connecting headphones to the radio. **IMPORTANT:** Excessive sound pressure from earphones and headphones can cause hearing loss.




To prevent possible hearing damage, do not listen at high volume levels for long periods.

Display and Audio



Tuning




Select/Snooze

System Settings	
Equaliser	>
Streaming Audio Quality	>
Network	>
Time/Date	>
Brightness	>
Inactive Standby	

Brightness	
On level	>
Standby level	>

Brightness	
High	*
Medium	
Low	



Line out socket (3.5mm Jack)

A 3.5mm **Line Out** socket located on the rear of your radio is provided for connecting the audio signal to an external amplifier. Inserting an audio cable into this socket will not mute the internal loudspeaker. Set the volume control on the radio to minimum if desired.




Auxiliary input socket

A 3.5mm **Auxiliary Input** socket located on the rear of your radio is provided for connecting the audio signal from an external audio source such as an MP3 or CD player.

1. Connect a stereo lead from the headphone output of your MP3 or CD player to the Aux In socket located at the rear of the radio. Typically this lead will have a 3.5mm stereo plug at both ends.
2. Switch on your radio and press the **Mode** button until **AUX in** mode is shown on the display.
3. Press 'play' on the connected audio device. If you are using its headphone output for the connection, set its volume control to a level of somewhere between two-thirds and maximum (the objective is to get a strong audio signal but without too much distortion). Then adjust the volume on the radio as required.

Note, if using an iPod as the sound source, you may need to set its output to maximum to get an adequate audio signal level.

4. After use, disconnect your player in order to listen to your radio conventionally.



Inactive Standby feature

In order to minimise its energy consumption when not in use, your radio includes an automatic Inactive Standby feature. This is designed to put your radio into standby if it detects that it is no longer being used in the following circumstances.

Internet radio – streaming is stopped;

Streaming Services – streaming is stopped; Aux-in / Bluetooth – there is no audio input signal

If any of these conditions is detected for more than 10 minutes then the radio will start a 5 minute countdown before entering standby. The display will show the time remaining. After 15 minutes of inactivity the radio will enter standby with the clock being displayed.

Pressing any button or resuming listening during the 15 minute period will reset the standby timer.


Standby in 5 minutes
Please press
any button to cancel.




Factory reset

If you wish to completely reset your radio to its initial state this may be performed by following this procedure. By performing a factory reset, all user entered settings will be erased.



1. With your radio switched on, Press **Menu**.
2. Choose 'System Settings', 'Factory Reset' and then 'YES' to proceed.
If you do not wish to carry out a system reset, highlight 'NO' and then press the control. The display will revert to the previous menu.
3. With 'YES' highlighted, press **Tuning**. A full reset will be performed and the radio will restart as if first plugged in. The DAB stations list together with any preset stations will be erased and your wireless network connection details will be lost. All configuration settings will be restored to their defaults, the clock and alarms will be reset.



Tuning



Select/Snooze



Electro-magnetic compatibility advice

In the event of a malfunction due to electrostatic discharge, mains power supply transients or short interruptions, reset the product as above to resume normal operation. If you are not able to perform the reset operation as above, removal and reconnection of the power supply may be required.

If the product is used in an environment with any ESD Immunity / Radiated Immunity / Conducted Immunity disturbance, the product may malfunction. It will automatically recover to normal when the ESD Immunity / Radiated Immunity / Conducted Immunity disturbance is stopped.

Product markings

	DC Voltage Power input 12V / 2.5A USB output 5V / 500mA
	Recycling This product bears the selective sorting symbol for Waste Electrical and Electronic Equipment (WEEE). This means that this product must be handled pursuant to European directive 2012/19/EU in order to be recycled or dismantled to minimize its impact on the environment. The user has the choice to give the product to a competent recycling organization or to the retailer when buying a new electrical or electronic equipment.



Software update

From time to time, new software features for your radio may be developed. Your radio has therefore been designed to allow its internal software to be updated using your Internet connection. You should not attempt to update your radio unless it is recommended to you by Roberts Customer Services. Updating the software may remove all network settings, radio station presets and alarm settings from your radio. It is important that you do not attempt this procedure unless you have a good Internet connection and a reliable mains power supply. If the radio connects to your router using a WiFi connection, make sure that this is also reliable before proceeding.

1. The '*Software update*' option is accessed via the System Settings menu. When you select '*Software update*' the menu will display '*Auto check setting*' and '*Check now*'. If you want your radio to check periodically for new software versions choose '*Auto check settings*' and then choose '*YES*'. If you do not want your radio to check for updates choose '*NO*'.
2. To check if there are any software updates available currently, choose '*Check now*'. The radio will check to see if an update is available. The display will show '*Checking for new versions*'. If there are no updates then the display will show '*Software up to date*'. If a software update is available your radio will then offer the choice of updating the software or not, displaying '*New version available. Update software?*'. Select the '*YES*' option if you wish to go through the update process. If you choose to update your radio it will first download the new software and will then reprogram its internal memory. This may take anything from a few seconds to a few minutes depending on the speed of your internet connection.
3. Once the software update is completed, the radio will prompt you to press **Select** to restart. Press **Tuning** and your radio will then restart. You may find that you will need to reconfigure your network connection following an update. You may also need to re-enter all radio station presets, alarm settings, and configuration options.

VERY IMPORTANT: Do not switch off the power to the radio until the update operation is complete and the radio has restarted, otherwise the unit may become permanently damaged.

Network profiles

Each time that you connect your radio to a WiFi network, the radio will store the details of that connection (SSID, security key, DHCP/IP address settings) as a profile. Up to four such profiles are stored in the radio so that if the unit is used in multiple locations there is no need to enter the network settings when returning to a location previously visited. The radio stores the four most recent profiles in memory identified by their SSID. Normally the radio will attempt to connect to one of the stored profiles and only if it is unable to do so will you need to use the Network Wizard (see page 15).

In the event that you visit a location only once you may wish to delete the profile for the network in that location to avoid losing other profiles.

1. Press **Menu**. Choose '*System settings*', '*Network*' and then '*Network profile*'. Press **Tuning** to see the stored profiles. The profile which is currently in use (if any) is marked with an asterisk.
2. To remove a profile from memory, rotate **Tuning** to highlight the profile to be deleted and then press the control. The radio will offer a '*YES*' or '*NO*' selection. Choose '*YES*'. The selected profile will be deleted. Note that it is not possible to delete a profile which is currently in use.

System Settings	
Time/Date	>
Brightness	>
Inactive Standby	
Language	>
Factory Reset	
Software Update	>

Software Update
Auto-check setting
Check now

Software Update

Check periodically for new versions?

YES*

NO



The software version display is provided for reference and customer support purposes.

1. Press **Menu**. Choose 'System Settings' and then 'Info'. The display will show the software version and radio ID. Rotate **Tuning** to display further information.
2. Press **Menu** to exit.

System Settings
Inactive Standby
Language >
Factory Reset
Software Update >
Setup Wizard
Info

Info
0.1.2.3-abcde7a35
Radio ID:
012345A12A1B
Friendly Name:
Stream94L

Info
SW version:
ir-cui-FS2340-0000-0316
V4.6.8.5295e-EX5_2-1A1
1
Spotify version:
HEAD-v3.166.69-q24821f73

Friendly name


Your radio uses a Friendly Name so that it is identifiable within remote control software such as the UNDOK app and the Spotify app. By default, your radio's Friendly Name will be shown as the "Stream94L". If you would like to change this name to something more personalised you may either use the UNDOK app or follow the instructions below.

1. Press **Menu** and choose 'System Settings', 'Network' and then 'View settings'. The current network settings will be displayed.
2. Rotate **Tuning** until the IP address is showing on the display. This is the local IP address used by your radio on your network. In the example screen to the right the IP address is 192.168.1.27. Make a note of the IP address shown on your radio's display for the next stage.
3. Ensure that your computer is on the same network as the radio. On your computer enter the IP address noted above into the address bar of your web browser. For example, enter 192.168.1.27 followed by Return. This will allow you to view some of the radios settings and will allow you to change the friendly name. Type the new name in the box as shown and then click Apply to save the name. The new Friendly Name will now be visible to network connected devices.

View settings
DHCP enable
SSID:
Julia S
IP address:
192.168.1.27
Subnet mask:

System Information

Friendly Name:	Roberts Stream 94i 002261111111	
New Friendly Name:	Julia's Stream 94i	<input type="button" value="Apply"/>
Firmware:	ir-mmi-FS2026-0500-0	
Radio ID:	002261111111	

Troubleshooting

If you experience any trouble with your radio, then you may find it useful to visit the help section on our web site.

If you have difficulty connecting the radio to your computer network, some of these steps may help to resolve the problem:

1. Confirm that a WiFi connected PC can access the Internet (i.e. can browse the web) using the same network.
2. Check that a DHCP server is available (normally a router function). Your radio will by default use DHCP unless you choose to disable it. This may be configured using the menu items '*System Settings*' -> '*Network*' -> '*Manual settings*'. For wireless you then need to choose '*DHCP enable*' or '*DHCP disable*'. If you enable DHCP then the radio will negotiate with your router (or DHCP server) and will be provided with an IP address as well as the other settings needed. If you wish to set the network configuration manually, refer to paragraph 6.
3. Check that your network's firewall is not blocking any outgoing ports. As a minimum, the radio needs access to UDP and TCP ports 80 and 123. Some Internet radio services may require additional ports to be open.
4. Check that your access point does not restrict connections to particular MAC addresses (sometimes called MAC address filtering).

You can view the radio's MAC address using the menu items '*System Settings*' -> '*Network*' -> '*View settings*' -> '*MAC address*'.

The MAC address will typically be of the form

00 : 22 : 61 : xx : xx : xx

5. If you have an encrypted network, check that you have entered the correct encryption key into the radio. Remember that text-format WPA keys are case sensitive. If your radio displays '*Network error*' when attempting to connect to an encrypted network, then please ensure that you enter the correct key for the network. If the problem persists, then you may need to re-check your network configuration.
6. If you need to set up your radio's IP address manually, you will need to know low-level details of your network's configuration. Use the menu items '*System Settings*' -> '*Network*' -> '*Manual settings*' -> '*Wireless*' (as needed) -> '*DHCP disable*'.

The radio will then prompt you in turn for the

IP address

Subnet mask

Gateway address

Primary DNS

Secondary DNS

If you are setting up a wireless connection manually you will also need to enter the SSID, the encryption type, and the encryption key.

[See page 16 for full details on how to set up your radio's network configuration manually.](#)



If your radio can connect to the network, but is unable to play a particular Internet radio station, it may be due to one these causes:

1. The station is not broadcasting at this time of the day.
2. The station has reached its maximum allowed number of simultaneous connections.
3. The Internet connection between your radio and the server (often located in a different country) is slow. This could be due to internet congestion, either locally or at a distance.
4. The station may choose to block internet connections to your geographic region (sometimes known as geo-locking).
5. The station is no longer broadcasting. The database of radio stations that your radio connects to is frequently updated and checked but may not always be completely accurate.
6. The radio station is broadcasting using an audio format which is not playable by your radio.

Try using a computer or phone to listen via the broadcaster's web site. If you can play the station with another device, it may be that the internet feed or local network connection is poor. However, some broadcasters (such as the BBC) provide different data streams for mobile users and Internet radio listeners, so this test is not always conclusive.

If you cannot play the station via your device this may indicate that the problem is not necessarily due to your radio, but it could be your network, your internet connection, the broadcaster, or internet congestion.



Cautions

Do not allow your radio to be exposed to water, steam or sand.
Do not leave your radio where excessive heat could cause damage.
The name plate is located on the rear of the radio.

Specifications

Power Requirements
Mains Adaptor



230 volts ~ 50/60Hz
(use only supplied adaptor)

Remote Control Battery 1 x CR2025

Connectivity

WiFi 802.11 b, g, n or a supported with WEP
and WPA / WPA2 encryption

Compatible with 2.4 GHz and 5 GHz WiFi bands.
5 GHz Wi-Fi function: 5150 - 5350MHz, 5470 - 5725MHz and 5725 - 5875MHz
Max power < 20 dBm

Use restriction: This device is authorised in the following countries for indoor use
only when used with 5GHz Wi-Fi (5150 to 5350MHz; channels 36 to 64):



AT	BE	BG	CH	CY	CZ	DE
DK	EE	EL	ES	FI	FR	HR
HU	IE	IS	IT	LI	LT	LU
LV	MT	NL	NO	PL	PT	RO
RS	SE	SI	SK	TR	UK(NI)	

Frequency Coverage

FM 87.5 - 108MHz
DAB 174.928 - 239.200MHz

Bluetooth 4.2 frequencies 2.402 - 2.480GHz, Power 4 dBm

- The AC/DC adaptor and radio shall not be exposed to dripping or splashing and no objects filled with liquids, such as vases, shall be placed on the AC/DC adaptor or the radio.
- It is recommended to operate the product such that there is a minimum distance (10cm recommended) to adjacent objects in order to ensure good ventilation.
- The ventilation of the product should not be restricted by covering it with items such as newspapers, tablecloths, curtains etc.
- No naked flame sources such as lighted candles should be placed on the product.
- It is recommended to avoid using or storing the product at extremes of temperature. Avoid leaving the unit in cars, on window sills, in direct sunlight etc.
- The AC/DC adaptor and radio must be used in a moderate climate.
- There are no user serviceable parts inside this product.
- Do not attempt to disassemble any part of the product.
- To maintain the compliance with the WiFi RF exposure requirement, place the product at least 20 cm (8 inches) from nearby persons except when operating the controls.

Headphone socket 3.5mm diameter, stereo
Aux In socket 3.5mm diameter, stereo
Line out socket 3.5mm diameter, stereo

Aerial System WiFi Built-in antenna
DAB/FM Telescopic aerial

Bluetooth standards A2DP, AVRCP
Bluetooth codecs supported SBC

Operating temperature range +5°C to +40°C

The Company reserves the right to amend the specification without notice.



Use of the software in this radio is subject to software licence terms contained in this user manual - by using the radio, you are agreeing to comply with these licence terms:

Thompson Licensing: MP3 audio decoder

MPEG Layer-3 audio coding technology licensed from Fraunhofer IIS and Thomson

Fraunhofer: MPEG-4 HE AAC Audio decoder

MPEG-4 HE-AAC audio coding technology licensed by Fraunhofer IIS:

<http://www.iis.fraunhofer.de/amm/>

**Microsoft: Windows Media Audio decoder (WMA)**

This product is protected by certain intellectual property rights of Microsoft. Use or distribution of such technology outside of this product is prohibited without a license from Microsoft.

Microsoft: Real Time Streaming Protocol (RTSP)

This product is protected by certain intellectual property rights of Microsoft. Use or distribution of such technology outside of this product is prohibited without a license from Microsoft.



Guarantee

This product is guaranteed for twenty four months from the date of purchase by the original owner against failure due to faulty workmanship or component breakdown, subject to the procedure stated below. Should any component or part fail during this guarantee period it will be repaired or replaced free of charge.

The guarantee does not cover:

1. Damage resulting from incorrect use.
2. Consequential damage.
3. Product with removed or defaced serial numbers.

N.B. Damaged or broken telescopic aerials will not be replaced under guarantee.

Procedure:

Any claim under this guarantee should be made through the dealer from whom the product was purchased. It is likely that your Roberts' dealer will be able to attend to any defect quickly and efficiently, but should it be necessary the dealer will return the product to the company's service department for attention. In the event that it is not possible to return the product to the Roberts dealer from whom it was purchased, please contact Roberts Radio using the contact details on the www.robertsradio.com website.

For product repairs falling outside the guarantee period, please refer to the "Customer care" tab on the www.robertsradio.com website.

These statements do not affect the statutory rights of a consumer.

Designed & Engineered in the UK
Made in China

ROBERTS RADIO LIMITED

Roberts Radio Ltd, Stoney Lane, Whiston, Prescot, L35 2XW, UK
Glen Dimplex Europe Ltd, Airport Road, Cloghran, Co. Dublin, K67 VE08, Ireland

www.robertsradio.com

© 2022 Roberts Radio Limited



Issue 2

April 2022

